



FC/UPC to FC/UPC, Tight Buffered Cable, Riser Rated,  
3.0mm, Singlemode 9/125um, Bend Insensitive

10-6325-ML

## Product Description

How do you stand out from other Fiber Optic Assembly suppliers? By configuring your jumpers online and simply sending a RFQ. Our team is standing by to offer fast accurate quotes and initiate our quick ship program. Multilink's Surelight Connectivity Solutions incorporate Telcordia compliant components and meet or exceed GR326-CORE specifications. Our manufacturing process includes using bend insensitive fiber cable and endface geometry testing. From singlemode to multimode, our online fiber configurator offers a unique way for fast and accurate turn around, allowing more productivity in a day.

## Specifications

Parameter	Specification
Connector Type:	FC/UPC
Fiber Category:	Singlemode (OS1)
Ferrule Material:	Zirconia
Housing Material:	Metal
Housing Color:	N/A
Boot Color:	Blue
Insertion Loss Typical:	0.12 dB

<b>Application:</b>	Riser Rated Indoor Horizontal General Building Applications
<b>Cable Length:</b>	1 Meter
<b>Cable Type:</b>	Singlemode 3.0mm Simplex 9/125µm Tight Buffered Bend In-sensitive G657 A1
<b>Flame Rating:</b>	Riser Rated OFNR
<b>Cable Assesmbly Type:</b>	Single Fiber
<b>Fiber Count:</b>	1
<b>Outer Jacket Color:</b>	Yellow
<b>Nominal Outside Diameter:</b>	3.0mm
<b>Polish #1:</b>	UPC
<b>Reflectance, Typical #1:</b>	< -58 dB
<b>Polish #2:</b>	UPC
<b>Reflectance, Typical #2:</b>	< -58 dB

**Contact Us**

North America	Europe, Middle East & Africa	Latin & South America
Tel: +1 440 366 6966 Fax: +1 440 366 6802 Email: <a href="mailto:engsupport@gomultilink.com">engsupport@gomultilink.com</a>	Tel: +1 440 366 6966 Fax: +1 440 366 6802 Email: <a href="mailto:engsupport@gomultilink.com">engsupport@gomultilink.com</a>	Tel: +1 954 499 9203 Mobile: +1 305 684 2388 Email: <a href="mailto:hquinones@gomultilink.com">hquinones@gomultilink.com</a>

# **Multilink**®

*Innovation At Work*



Multilink Inc.  
 580 Ternes Ln  
 Elyria, OH 44035  
 Tel: (440) 366-6966  
 Fax: (440) 366-6802



[facebook.com/GoMultilink](https://facebook.com/GoMultilink)



[twitter.com/GoMultilink](https://twitter.com/GoMultilink)



[youtube.com/GoMultilink](https://youtube.com/GoMultilink)

© Multilink Inc. 2016 • All Rights Reserved

Contact Us |

North America	Europe, Middle East & Africa	Latin & South America
Tel: +1 440 366 6966 Fax: +1 440 366 6802 Email: <a href="mailto:engsupport@gomultilink.com">engsupport@gomultilink.com</a>	Tel: +1 440 366 6966 Fax: +1 440 366 6802 Email: <a href="mailto:engsupport@gomultilink.com">engsupport@gomultilink.com</a>	Tel: +1 954 499 9203 Mobile: +1 305 684 2388 Email: <a href="mailto:hquinones@gomultilink.com">hquinones@gomultilink.com</a>