NG4-VDKR1MQA20001L



NG4access® Module VAM, DWDM, 40 channels, 100 GHz channel spacing, starting channel 20, 1 circuit, Mux, LC/UPC, right, 1 test port

- VAMs help enhance optical transport systems by providing flexible, easy to incorporate optical components into the network
- VAMs increase fiber capacity and help troubleshooting or distributing signals to multiple subscribers
- *Product complies with the Build America, Buy America Act (BABAA) requirements of the Infrastructure Investment and Jobs Act of 2021 (Pub. L. 117- 58, §§ 70901-70953), or is the subject of a waiver approved by the Secretary of Commerce or designee. Compliance requirements and waiver applicability vary based on government funding program. Check the laws and regulations for your specific program.

Product Classification

Regional Availability Latin America | North America

PortfolioCommScope®Product TypeDWDM moduleProduct BrandNG4access®Product SeriesFACT | NG4

Government RequirementsBuild America Buy America (BABA) compliant*

General Specifications

Device Type Plug-and-play module

Functionality Multiplexing

Application For use with NG4 access frames

Circuits, quantity 1

Distribution Type 40-channel DWDM

Interface, frontLC/UPCInterface, InputLC/UPCInterface, OutputLC/UPC

Location of Manufacturing Waived per BABA waiver for BEAD Program

Multiplexers, quantity 1

Port Type, optional Test port

Tray Orientation Right orientation

COMMSC PE®

NG4-VDKR1MQA20001L

Dimensions

 Height
 13.21 mm | 0.52 in

 Width
 159.77 mm | 6.29 in

 Depth
 130.3 mm | 5.13 in

Optical Specifications

Channel Spacing 100 GHz
Starting Channel Number 20

Packaging and Weights

Packaging quantity 1

